

5 Minute Guide to HiPath 3300 and 3350

Overview of the Siemens HiPath 3300 and 3350

The IP convergence systems HiPath 3300 and HiPath 3350 V8 offer SME businesses of 10 to 96 subscribers high reliability voice communications using high quality terminals with easy operation.

HiPath 3300 and 3350 provides:

- Unified Communications Applications (OpenScape Office)
- Open interfaces for the integration of external applications
- Mobility options for mobile employees



	HiPath 3300 Rack Mount (19")	HiPath 3350 Wall Mount	Comments
Max Digital Users	24	24	8 supplied on CB
Max Analogue Users	20	36	4 supplied on CB
Max IP Users	96	96	Via HG1500 card
Max Cordless users	16	16	Using DECT lite
optiClient Attendant	4	4	
Integrated Voicemail boxes	24	24	
ISDN2 B Channels	16	16	2 supplied on CB
IP Trunks	16	16	Via HG1500 card
Slots for blades	2	2	

Unified Communication applications (OpenScape Office)

OpenScape Office is a server-based application portal for HiPath 3000. A program of individual licensing permits different applications to be scaled according to customer requirements and put into operation. OpenScape Office is only released in stand alone scenarios. HiPath systems connected to OpenScape Office cannot be integrated into Hi-Path networks.

OpenScape Office supports the following functions and features:

Presence

You can then tell if someone is in a meeting, conducting a call, when they will be again available and how best to reach them. Presence status can be changed via telephone or online when you are away from the office

myPortal

Every staff member has access to the entire range of communication resources over a single screen. They can use this application to read, manage and answer e-mail, voicemail, fax and instant messages.

myAttendant

Offers selective subscribers a user-friendly attendant, including information the Presence status.

VoiceMail

Messages from your mobile phone and landline can be forwarded to your HiPath OpenOffice voicemail box.

Fixed Mobile Convergence

Employees only need a single phone number their office number. They can also be reached on their mobile or home office phones via this number. When an employee makes an outgoing call from a mobile or home office phone, his or her office number is displayed as the origin on the called party's terminal.

Configuring the Siemens HiPath 3300 and 3350

The HiPath 3300 and 3350 CCU includes 8 digital extensions, 4 analogue extensions, 2 (4 channels) BRI circuits and EVM (integrated voicemail). Both the 3300 and 3350 have 2 slots available for expansion.

Stage 1: Select the HiPath 3300 or 3350 basic system

Select the base system that you require and then add a power cord

L30251-U600-G476	Hipath 3350 V8 Wall mount Basic System
L30251-U600-G470	HiPath 3300 V8 for 19" Rack Basic System
L30251-U600-A390	Mains Power Cord, 25m, UK

Stage 2: Adding extensions and handsets

Add TDM extension blades to increase the number of digital and analogue extensions up from the base number that are included in the basic bundle as required. The 3350 has a 16 port analogue blade available for larger analogue installations. Remember that there are only 2 slots for expansion! Consult your price book for part codes.

If IP extensions are required then you will need to include a HG1500 card. This consumes 1 of the 2 available expansion slots.

L30251-U600-A647	HG 1500 V3.0 Basic Package (with 8 B-channels) for HiPath 3300/3500
L30251-U600-A648	HG 1500 V3.0 Basic Package (with 8 B-channels) for HiPath 3350/3550

Each HG1500 card includes 8 B-channels which are used for IP to TDM conversion. If you require more B-channels these can be provided with the addition of a single PDM1 expansion daughterboard and licenses (max 16):.

L30251-U600-A305	PDM1 Expansion Module for HG 1500 V3.0
L30250-U622-B352	HG1500 V3 Expansion: 1 Additional B-Channel for HiPath 3000 V8

Finally add the appropriate number of IP extension licenses (max 96).

L30250-U622-B350	IP Workpoints Licenses for HiPath 3000 V8
------------------	---

Stage 3: Adding trunking

Add analogue or digital trunking as required. Remember that each expansion board will consume 1 of your 2 available slots. Consult your price book for part codes.

Stage 4: Adding applications

The HiPath 3300 and 3350 does not include integrated OpenScape Office and needs a separate server and licenses. Also be aware that OpenScape Office requires a HG1500 card and B-channels..

L30250-U622-B378	OpenScape Office V2 Basic License Package for HiPath 3000/5000 V8 including 10 OpenScape Office standard licenses
L30251-U600-A676	OpenScape Office V2 Software DVD
L30250-U622-B360	OpenScape Office V2 Standard User-License for HiPath 3000/5000 V8
L30250-U622-B361	OpenScape Office V2 myPortal for Outlook, for HiPath 3000/5000 V8

